

HBO MPEG-4 HD Technical Information

Updated as of January 2012

Satellite and Transponder Chart

Satellite/Transponder/ Virtual Channel Table Number	Feed	Receiver	Ch	MPEG Svc ID	Pol	Center Freq MHz	L- Band Freq MHz
Galaxy 15 (133° W) Transponder 19 VCT# 812 DVB-S2, 8PSK Symbol Code/ Bit Rate 30.0, 5/6	HBO HD East	DCII ¹	441	80	H	4080	1070
	HBO 2 HD East		442	81	H	4080	1070
	HBO Signature HD East		443	82	H	4080	1070
	HBO Family HD East		444	83	H	4080	1070
	HBO Latino HD East		445	84	H	4080	1070
	Cinemax HD East		446	85	H	4080	1070
	MoreMAX HD East		447	86	H	4080	1070
	ActionMAX HD East		448	87	H	4080	1070
Galaxy 14 (125° W) Transponder 16 VCT# 813 DVB-S2, 8PSK Symbol Code/ Bit Rate 30.0, 5/6	HBO HD West	DCII ¹	461	101	V	4020	1130
	HBO 2 HD West		462	102	V	4020	1130
	HBO Signature HD West		463	103	V	4020	1130
	HBO Family HD West		464	104	V	4020	1130
	HBO Latino HD West		465	105	V	4020	1130
	Cinemax HD West		466	106	V	4020	1130
	MoreMAX HD West		467	107	V	4020	1130
	ActionMAX HD West		468	108	V	4020	1130
Galaxy 14 (125° W) Transponder 8 VCT# 816 DVB-S2, 8PSK Symbol Code/ Bit Rate 30.0, 5/6	HBO Comedy HD East	DCII ¹	481	120	V	3860	1290
	HBO Comedy HD West		482	121	V	3860	1290
	HBO Zone HD East		483	122	V	3860	1290
	HBO Zone HD West		484	123	V	3860	1290
	ThrillerMAX HD East		485	124	V	3860	1290
	ThrillerMAX HD West		486	125	V	3860	1290
	WMAX HD East		487	126	V	3860	1290
	@MAX HD East		488	127	V	3860	1290
	5StarMAX HD East		489	128	V	3860	1290
	OuterMAX HD East		490	129	V	3860	1290

¹ Receivers: DSR-4410MD - Multi-decrypt MPEG-4 TS
 DSR-6050 - Single decrypt Transcoder (MPEG-4 HD to MPEG-2 HD)
 DSR-6300 - Multi-decrypt Transcoder (3 MPEG-4 HD to 3 MPEG-2 HD)*

*The HBO uplink controls the VCT and VCN selection for the DSR-6300 based on the feeds approved for authorization on the start-up form.