

HBO Satellite and Transponder Chart - Linear HD and SVOD HD/SD - 4/16/2010

Satellite/Transponder Virtual Channel Table Transmission Mode	Feed or Content Model	Transmit Signal	VCN (CH)	MPEG ID	Video PID	Eng Audio PID	Esp Audio PID	Pol	Center Freq MHz	L-band Freq MHz
Galaxy 13 (127° W) Transponder 10 VCT# 112 (MPEG-2) Symbol Code / Bit Rate 29.3, 7/8 Split	HBO HD E – (I)	DCI ¹	151	51	400	401	402	H	3900	1250
	HBO HD W – (Q)		162	62	464	465	466			
Galaxy 13(127° W) Transponder 11 VCT# 730 (MPEG-2) Symbol Code / Bit Rate 29.3, 7/8 Combined	Cinemax HD E MPEG-2	DCI ²	153	53	464	465	466	V	3920	1230
	Cinemax HD W MPEG-2		164	64	528	529	530			
Galaxy 12 (133° W) Transponder 19 VCT# 812 (MPEG-4) DVB-S2, 8PSK Symbol Code/ Bit Rate 30.0, 5/6	HBO HD E	DVB-S2 ³	441	80	273	274	275	H	4080	1070
	HBO 2 HD E		442	81	289	290	291			
	HBO Signature HD E		443	82	305	306	307			
	HBO Family HD E		444	83	321	322	323			
	HBO Latino HD E		445	84	337	338	339			
	Cinemax HD E		446	85	353	354	355			
	MoreMAX HD E		447	86	369	370	371			
	ActionMAX HD E		448	87	385	386	387			
Galaxy 14 (125° W) Transponder 15 DVB-S2, 8PSK Symbol Code/ Bit Rate 30.0, 3/4	Ericsson (Tandberg) NextGen Catcher Required	DVB-S2 ⁴	N/A (Catcher is pre-configured)					H	4000	1150
	HBO OD SD									
	Cinemax OD SD									
	HBO OD HD									
	Cinemax OD HD									
Galaxy 14 (125° W) Transponder 16 VCT# 813 (MPEG-4) DVB-S2, 8PSK Symbol Code/ Bit Rate 30.0, 5/6	HBO HD W	DVB-S2 ³	461	101	273	274	275	V	4020	1130
	HBO 2 HD W		462	102	289	290	291			
	HBO Signature HD W		463	103	305	306	307			
	HBO Family HD W		464	104	321	322	323			
	HBO Latino HD W		465	105	337	338	339			
	Cinemax HD W		466	106	353	354	355			
	MoreMAX HD W		467	107	369	370	371			
	ActionMAX HD W		468	108	385	386	387			
Galaxy 14 (125° W) Transponder 8 VCT# 816 (MPEG-4) DVB-S2, 8PSK Symbol Code/ Bit Rate 30.0, 5/6	HBO Comedy HD E	DVB-S2 ³	481	120	273	274	275	V	3860	1290
	HBO Comedy HD W		482	121	289	290	291			
	HBO Zone HD E		483	122	305	306	307			
	HBO Zone HD W		484	123	321	322	323			
	ThrillerMAX HD E		485	124	337	338	339			
	ThrillerMAX HD W		486	125	353	354	355			
	WMAX HD E		487	126	369	370	371			
	@MAX HD E		488	127	385	386	387			
	5StarMAX HD E		489	128	401	402	403			
	OuterMAX HD E		490	129	417	418	419			

¹ All current Motorola DigiCipher II IRDs including DSR-4410, DSR-4410MD, DSR-4530 and DSR-4550.

² All current Motorola DigiCipher II IRDs that support MegaPipe+ (MPP) including DSR-4410, DSR-4410MD, DSR-4530, and DSR-4550.

³ DVB-S2 capable Motorola IRDs, DSR-4410 MD (MPEG-4 multi-decrypt output), DSR-6300 (MPEG-4 three service multi-decrypt output), or DSR-6050 (Transcoded MPEG-4 to MPEG-2 single-decrypt output).

⁴ Only the Ericsson (Tandberg) Next Generation catcher model NG-CAT-HBO can receive HOD and MaxOD (SD and HD) from this transponder. No IRD is required, as the internal receiver of the catcher is preconfigured by Ericsson to receive the satellite signal.